

UNITED STATES PATENT APPLICATION

for

**METHOD AND APPARATUS FOR PERFORMING SELECTIVE
QUANTIZATION BY MANIPULATION OF REFINEMENT BITS**

Inventors:

Edward L. Schwartz

Michael J. Gormish

Martin Boliek

Gene K. Wu

prepared by:

BLAKELY, SOKOLOFF, TAYLOR & ZAFMAN LLP

12400 Wilshire Boulevard

Los Angeles, CA 90025-1026

(408) 720-8598

File No.: 74451.P127D6

EXPRESS MAIL CERTIFICATE OF MAILING


"Express Mail" mailing label number: EL672748355US

Date of Deposit: March 6, 2001

I hereby certify that I am causing this paper or fee to be deposited with the United States Postal Service "Express Mail Post Office to Addressee" service on the date indicated above and that this paper or fee has been addressed to the Assistant Commissioner for Patents, Washington, D. C. 20231

Mara E. Brown

(Typed or printed name of person mailing paper or fee)


(Signature of person mailing paper or fee)

3/6/01
(Date signed)

METHOD AND APPARATUS FOR PERFORMING SELECTIVE QUANTIZATION BY MANIPULATION OF REFINEMENT BITS

This is a divisional of application Serial No. _____, filed on
February 15, 2001, entitled "A Memory Usage Scheme for Performing
5 Wavelet Processing," and assigned to the corporate assignee of the present
invention.

FIELD OF THE INVENTION

The present invention relates to the field of compression and
10 decompression; more particularly, the present invention relates to
performing selective quantization by manipulation of refinement bits.

BACKGROUND OF THE INVENTION

The new JPEG 2000 decoding standard (ITU-T Rec.T.800/ISO/IEC
15 154441:2000 JPEG 2000 Image Coding System) provides a new coding
scheme and codestream definition for images. Although the JPEG 2000
standard is a decoding standard, the JPEG 2000 specifies encoding and
decoding by defining what a decoder must do. Under the JPEG 2000
Standard, each image is divided into one or more rectangular tiles. If there
20 is more than one tile, the tiling of the image creates tile-components that can

be extracted or decoded independently of each other. Tile-components
comprise all of the samples of a given component in a tile. An image may
have multiple components. Each of such components comprises a two-
dimensional array of samples. For example, a color image might have red,
5 green and blue components.

After tiling of an image, the tile-components may be decomposed into
different decomposition levels using a wavelet transformation. These
decomposition levels contain a number of subbands populated with
coefficients that describe the horizontal and vertical spatial frequency
10 characteristics of the original tile-components. The coefficients provide
frequency information about a local area, rather than across the entire image.
That is, a small number of coefficients completely describe a single sample.
A decomposition level is related to the next decomposition level by a spatial
factor of two, such that each successive decomposition level of the subbands
15 has approximately half the horizontal resolution and half the vertical
resolution of the previous decomposition level.

Although there are as many coefficients as there are samples, the
information content tends to be concentrated in just a few coefficients.
Through quantization, the information content of a large number of

coefficients is further reduced. Additional processing by an entropy coder reduces the number of bits required to represent these quantized coefficients, sometimes significantly compared to the original image.

The individual subbands of a tile-component are further divided into
 5 code-blocks. These code blocks can be grouped into partitions. These rectangular arrays of coefficients can be extracted independently. The individual bit-planes of the coefficients in a code-block are entropy coded with three coding passes. Each of these coding passes collects contextual information about the bit-plane compressed image data.

10 The bit stream compressed image data created from these coding passes is grouped in layers. Layers are arbitrary groupings of successive coding passes from code-blocks. Although there is great flexibility in layering, the premise is that each successive layer contributes to a higher quality image. Subband coefficients at each resolution level are partitioned
 15 into rectangular areas called precincts.

Packets are a fundamental unit of the compressed codestream. A packet contains compressed image data from one layer of a precinct of one resolution level of one tile-component. These packets are placed in a defined order in the codestream.

The codestream relating to a tile, organized in packets, are arranged in one, or more, tile-parts. A tile-part header, comprised of a series of markers and marker segments, or tags, contains information about the various mechanisms and coding styles that are needed to locate, extract,
 5 decode, and reconstruct every tile-component. At the beginning of the entire codestream is a main header, comprised of markers and marker segments, that offers similar information as well as information about the original image.

The codestream is optionally wrapped in a file format that allows
 10 applications to interpret the meaning of, and other information about, the image. The file format may contain data besides the codestream.

The decoding of a JPEG 2000 codestream is performed by reversing the order of the encoding steps. Figure 1 is a block diagram of the JPEG 2000 standard decoding scheme that operates on a compressed image data
 15 codestream. Referring to Figure 1, a bitstream initially is received by data ordering block 101 that regroups layers and subband coefficients.

Arithmetic coder 102 uses contextual information collected during encoding about the bit-plane compressed image data, and its internal state, to decode a compressed bit stream.

After arithmetic decoding, the coefficients undergo bit modeling in coefficient bit modeling block 103. Next, the codestream is quantized by quantization block 104, which may be quantizing based on a region of interest (ROI) as indicated by ROI block 105. After quantization, an inverse
5 transform is applied to the remaining coefficients via transform block 106, followed by DC and optional component transform block 107. This results in generation of a reconstructed image.

The JPEG2000 standard leaves many choices to implementers.

SUMMARY OF THE INVENTION

A method and apparatus for performing selective quantization by manipulation of refinement bits is described. In one embodiment, the method comprises performing a refinement coding pass to bit-planes of a code block to create refinement bits and setting refinement bits to the more
5 probable symbol (MPS).

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be understood more fully from the detailed description given below and from the accompanying drawings of various embodiments of the invention, which, however, should not be taken
5 to limit the invention to the specific embodiments, but are for explanation and understanding only.

Figure 1 is a block diagram of the JPEG 2000 standard decoding scheme.

10

Figure 2 illustrates one embodiment of an organization for an image in memory.

Figures 3A-F illustrate a transform memory organization for various
15 levels depicting conceptually how coefficients may be stored for the forward (Figures A-C) and inverse (Figures 3D-F) transforms.

Figures 4A and B illustrate embodiments of a single memory where
the input image data and the various decomposition levels of the image data
20 can be stored during forward and inverse transforms, respectively.

Figure 5 illustrates one embodiment of the process of handling the input data.

Figure 6A illustrates a system having a progression order conversion
5 parser.

Figure 6B illustrates a progression converter converting from a resolution progressive codestream to a quality progressive codestream.

Figure 7A shows multiple ways to convert a codestream from one
10 progression order to another.

Figure 7B shows one embodiment of simplified conversion paths to convert a codestream from one progression order to another.

15

Figure 8 illustrates one embodiment of a process for performing progression order conversion.

Figure 9 illustrates a decoder that selects portions of a codestream based on sideband information.

Figure 10 is a flow diagram of a process for using layers when
5 decoding.

Figure 11 is a flow diagram of one embodiment of an editing process.

Figure 12 illustrates a bell-shaped curve of a range of values that are
10 quantized to a particular value.

Figure 13 is a flow diagram of one embodiment of a process to reduce
flicker.

Figure 14 illustrates one embodiment of an encoder (or portion
15 thereof) that performs the quantization to reduce flicker.

Figure 15A illustrates a process for performing rate control.

Figure 15B illustrates an exemplary number of layers that may be subjected to first and second passes.

Figure 16 illustrates one embodiment of the process for accessing the groupings of tile parts.

Figure 17 and 18 illustrate quantizers for one component for a three level 5,3 transform.

Figure 19 illustrates an example of HVS weighted quantization.

Figure 20 is a block diagram of one embodiment of a computer system.

Figure 21 illustrates an example progression with tile parts for a single server.

Figure 22 illustrates an example of layering for a 5,3 irreversible transform.

Figure 23 illustrates an example in which transform has 5 levels and the data is divided up into layers 0-3.

5 **Figure 24** illustrates one example of a situation in which flicker may be avoided in which values in first and third frames are used to set the value in the second frame.

10 **Figure 25** is a block diagram of a prior art decoding process that includes color management.

Figure 26 illustrates one embodiment of a non-preferred camera encoder.

15 **Figure 27** illustrates one embodiment of a simpler camera encoder.

Figure 28 is a flow diagram of one embodiment of a process for applying an inverse transform with clipping on partially transformed coefficients.

DETAILED DESCRIPTION OF THE PRESENT INVENTION

Improvements to compression and decompression schemes are described. It is a purpose of the techniques and implementations described herein to use choices in JPEG 2000 to make high speed, low cost, low
5 memory and/or feature rich implementations.

In the following description, numerous details are set forth in order to provide a thorough explanation of the present invention. It will be apparent, however, to one skilled in the art, that the present invention may be practiced without these specific details. In other instances, well-known
10 structures and devices are shown in block diagram form, rather than in detail, in order to avoid obscuring the present invention.

Some portions of the detailed descriptions which follow are presented in terms of algorithms and symbolic representations of operations on data bits within a computer memory. These algorithmic descriptions and
15 representations are the means used by those skilled in the data processing arts to most effectively convey the substance of their work to others skilled in the art. An algorithm is here, and generally, conceived to be a self-consistent sequence of steps leading to a desired result. The steps are those requiring physical manipulations of physical quantities. Usually, though

not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated. It has proven convenient at times, principally for reasons of common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities. Unless specifically stated otherwise as apparent from the following discussion, it is appreciated that throughout the description, discussions utilizing terms such as "processing" or "computing" or "calculating" or "determining" or "displaying" or the like, refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data similarly represented as physical quantities within the computer system memories or registers or other such information storage, transmission or display devices.

The present invention also relates to apparatus for performing the operations herein. This apparatus may be specially constructed for the

required purposes, or it may comprise a general purpose computer selectively activated or reconfigured by a computer program stored in the computer. Such a computer program may be stored in a computer readable storage medium, such as, but is not limited to, any type of disk including
5 floppy disks, optical disks, CD-ROMs, and magnetic-optical disks, read-only memories (ROMs), random access memories (RAMs), EPROMs, EEPROMs, magnetic or optical cards, or any type of media suitable for storing electronic instructions, and each coupled to a computer system bus.

The algorithms and displays presented herein are not inherently
10 related to any particular computer or other apparatus. Various general purpose systems may be used with programs in accordance with the teachings herein, or it may prove convenient to construct more specialized apparatus to perform the required method steps. The required structure for a variety of these systems will appear from the description below. In
15 addition, the present invention is not described with reference to any particular programming language. It will be appreciated that a variety of programming languages may be used to implement the teachings of the invention as described herein.

A machine-readable medium includes any mechanism for storing or transmitting information in a form readable by a machine (e.g., a computer).

For example, a machine-readable medium includes read only memory

("ROM"); random access memory ("RAM"); magnetic disk storage media;

- 5 optical storage media; flash memory devices; electrical, optical, acoustical or other form of propagated signals (e.g., carrier waves, infrared signals, digital signals, etc.); etc.

Overview

- 10 The following descriptions relate to implementations or novel ways to take advantage of the flexibility of JPEG 2000 or other coding schemes with similar features.

Memory Usage for Low Memory and Fast Burst Access

- 15 Figure 2 shows one embodiment of an organization for an image in memory 201. Referring to Figure 2, only the "tile height" raster lines, or a band of the image, are in memory 201, not the whole image. Thus, the amount of an image in memory 201 is equal to the image width multiplied

by the tile height. Inside the band of the image is at least one tile, such as tile 210.

The wavelet transform processing logic 202 includes memory access logic 202A to read data from and store data to memory 201 to enable
 5 wavelet transform 202B to be applied to the data (image data or coefficients depending on the level of coefficient). Wavelet processing logic 202 may comprise hardware, software or a combination of both.

In one embodiment, access logic 202A accesses the tile with four parameters: a pointer or index to the start of the tile in memory, the width of
 10 the tile, the height of the tile, and the line offset to get from the start of one line to another (the image width). Alternatively, access logic 202A accesses memory 201 using a pointer or index to the end of the tile instead of the width of the tile.

In one embodiment, in order to access for each line of a tile or a
 15 portion of a line of an image to perform some function F, the following process may be used.

```

    line = start
    for y = 0 to tile_height - 1
      for x = 0 to tile_width - 1
        perform function F with line[x]
  20      line = line + line_offset
  
```

One of the functions F may include applying a wavelet transform on pairs of lines. Also another function F may be a DC level shift, multiple component transform.

Such a process would be performed by processing logic that may
 5 comprise hardware (e.g., dedicated logic, circuitry, etc.), software (such as is run on a general purpose computer system or a dedicated machine), or a combination of both.

In one embodiment, coefficients from a subband are accessed using a similar scheme with a starting point, width, height and line offset. Because
 10 rows of coefficients are stored together in memory, rows may be accessed efficiently when stored in cache, burst accessible memories or memories that are wider than one coefficient.

Figures 3A-C show a transform memory organization for various levels depicting conceptually how coefficients may be stored. All LH, HL
 15 and HH coefficients (using the nomenclature of ITU-T Rec.T.800/ISO/IEC 15444:2000 JPEG 2000 Image Coding System) are coded. These coefficients are represented by dotted lines in Figures 3B and C. Input lines of input tile 301 and LL coefficients (shown as solid lines in Figures 3B and 3C in successive levels) only need to be stored temporarily while computing the

transform with the exception of the final transform level's LL coefficients which are coded. When a transform is used that does the horizontal and vertical transforms in one pass and uses line buffers, once a pair of input rows has been completely read (input lines or LL coefficients), the space
 5 used by lines can be reused.

Figures 3A-C show input tile 301, level 1 (L1)(302) and level 2 (L2)(303) memory areas aligned with an offset to indicate how reuse might be accomplished in one embodiment. The addition of two rows, rows 312 and 313, to the memory space used to hold input tile 301, is needed to
 10 generate the L1 coefficients when reusing the memory for input tile 301 for L1 coefficients. The addition of four rows, rows 341-342, to the memory space used to hold the L1 coefficients is needed to generate the L2 coefficients when reusing the memory storing the L1 coefficients for L2 coefficients. (Note that there are two rows between rows 341 and 342 that
 15 are wasted space.) The additional lines are preferably behind the direction the wavelet transform is being applied to the information in the memory.

More specifically, a pair of input rows input tile 301 corresponds to one row of each of LL, LH, HL and HH coefficients at level 1, resulting from the application of a transform to two different lines and the results of

applying the wavelet transform being written into lines of the memory. For example, the results of applying a wavelet transform to input rows 310 and 311 are the coefficients in portions of rows 312 and 313 of L1 coefficients (302). For example, LL coefficients 321 of row 312 corresponds to the LL coefficients (solid line) of level 1, HL coefficients 322 of row 312 corresponds to the HL coefficients of level 1, LH portion 323 of row 313 corresponds to the LH coefficients of level 1, and HH portion 324 corresponds to the HH coefficients of level 1. Note that the level 1 coefficients from the first two input lines are stored in two extra rows at the top of the memory with the remaining level 1 coefficients being written into the locations storing the data of input tile 301 to reuse the memory. The width and height for each type of coefficient (e.g., LH, HL, HH) for each subband of level 1 coefficients is half that of input tile 301. The line offset from the LL row to the next LL row for level 1 (e.g., the distance from row 312 to row 314 in Figure 3B) is twice the tile width (since each coefficient row is from an area corresponding to two lines).

Similarly, the results of applying the wavelet transform to two rows of LL coefficients at level 1 (solid lines) are the coefficients in two rows namely LL coefficients (331), LH coefficients (332), HL coefficients (333) and

HH coefficients (334) at level 2. The width and height for level 2 coefficients is a quarter that of input tile 301. The line offset for level 2 is four times the tile width (since each coefficient row is from an area corresponding to two level 1 LL rows or four input lines). Thus, four extra lines of memory are
5 needed to use the same memory that is storing the input tile to store the L2 coefficients. Note that if a third decomposition level was being performed, an additional 8 lines would be needed. Thus, in this example, a total of 14 extra lines are needed to enable reuse of the memory that stores an input time and has two levels of decomposition applied thereto. A general
10 formula may be used to determine the number of extra lines is as follows:

$$2^{(\text{maxlevel}+1)}-2.$$

To access subbands, such as the LL, LH, HL and HH subbands, only a starting pointer and the offset between rows/lines are necessary. The height and width are also needed to know when to stop when accessing a tile.

15 As the number of decomposition levels increases, some rows at the bottom of memory become unused. That is, the lines of memory below the L1 coefficients after the first decomposition level become unused, the lines of memory below the L2 coefficients after the second decomposition level become unused, etc. In one embodiment, this extra space may be reused.

Figures 3D-3F illustrate the corresponding inverse transform memory usage in which additional lines store the results of applying an inverse transform and those additional lines are in the memory behind the direction the inverse transform is being performed.

- 5 Figure 4A shows one embodiment of a single memory where the input and the various levels can be stored during application of a forward transform. Referring to Figure 4A, locations for the input tile, level 1 coefficients, level 2 coefficients, and level 3 coefficients is shown with the added 2, 4 and 8 lines respectively. Figure 4B shows a similar single
- 10 memory embodiment where the input coefficients of various levels of the transform can be stored along with the output during application of an inverse transform.

Table 1 shows the amount of memory required for various transform levels for a 256x256 tile for separate memories and reused memory.

Table 1

level	Separate memory (bytes)		reused memory (bytes)	
1	256x256 =	65,536	2x256 =	512
2	128x128 =	16,384	4x256 =	1,024
3	64x64 =	4,096	8x256 =	2,048
4	32x32 =	1,024	16x256 =	4,096
5	16x16 =	256	32x256 =	8,192
6	8x8 =	64	64x256 =	16,384

For reused memory, the amount listed is the additional new memory used for that level. For this example, reusing memory for levels 1, 2 and 3 saves memory. Level 4 may use a separate memory.

The memory for levels 4, 5 and 6 could be placed in a single memory after level 3 has been generated or in a completely different and separate memory. The amount of memory necessary is 38×32 , which is less than 5×256 . Because there are two unused lines after generating the level 1 coefficients (i.e., the memory that stored the last two lines of input data), a small memory savings can be achieved by letting the levels 4, 5 and 6 reuse these two lines. This is particularly important because the number of additional lines for levels 4, 5, and 6 is 16, 32 and 64, and the extra space between the lines will be twice as far and half as wide as the level before.

In one embodiment, coefficients from levels 4, 5, and 6 are packed in a smaller memory structure, such as storage area 450 in Figure 4. Referring to

Figure 4, the level 4 coefficients are stored in an area having a height equal to the tile height divided by 8 (2^3 where 3 corresponds to the number of levels) and a width equal to the tile width w divided by 8 (2^3 where 3 corresponds to the number of levels previously stored elsewhere). An

5 additional two lines 451 are all that is needed to store level 5 coefficients in the same necessary storage area. Similarly, an additional four lines is all that is necessary to accommodate using this memory storage area for the level 6 coefficients. Note that no lines are skipped when storing the coefficients. In one embodiment in which a 256x256 tile is being processed, the extra 5 lines
10 at the bottom of storage area 430, two lines 421 and approximately 4.75 lines 422 are used to accommodate storage area 450. As shown, the approximate by three lines 422 represent allocated memory or in addition to that necessary to store the input tile. In this manner, the storage area for the input tile is almost completely reused.

15 In one embodiment, to use a very little, or potentially minimum, memory, level 6 is stored separately from levels 4 and 5. However, this only saves 64 bytes of memory.

A memory a little smaller than 273x256 can hold all the transform coefficients for a 256x256 tile. This is less than 7% more than a true in-place

memory organization. Unlike an in-place memory organization, extra copies are avoided while simultaneously keeping the rows packed together for fast access.

Table 2 shows another example of using separate versus reused memory for 128x128 tiles. For this size, the first three transform levels can reuse memory in a 142x128 buffer.

Table 2

level	Separate memory (bytes)		reused memory (bytes)	
1	128x128 =	16,384	2x128 =	256
2	64x64 =	4,096	4x128 =	512
3	32x32 =	1,024	8x128 =	1024

In one embodiment, a decision to use in-place memory or new memory is a function of tile height and transform level. Such a decision may be based on the following:

if tile height $> 2^{(3 \cdot \text{level} - 2)}$, then use in-place method

if tile height $= 2^{(3 \cdot \text{level} - 2)}$, then either may be used

if tile height $< 2^{(3 \cdot \text{level} - 2)}$, then use new memory

15

To illustrate the application of the decision, Table 3 below:

Table 3

level	$2^{(3 \cdot \text{level} - 2)}$
1	2
2	16
3	128
4	1024
5	8192

In some applications, adapting the memory organization to the tile height is inconvenient. A single fixed memory organization can be used.

- 5 Tile sizes smaller than 128x128 typically result in bad compression performance, so would typically not be used. While tile sizes bigger than 1Kx1K can be used for very large images, this does not significantly improve compression and the large amount of memory required would typically be burdensome. Therefore, assuming a tile height between 128 and 1024
- 10 inclusive and using in-place memory for 3 levels of the transform is a good heuristic.

- Decoding is similar in that the results of applying an inverse transform are written ahead of where the decoding processing logic is reading, with the only notable difference being that the start is from the
- 15 highest level to the lowest level, such as level 6 to level 1 in the example above. In such a case, the input tile ends up at the top of the memory

structure. The extra lines to accommodate the memory reuse are in decreasing order. For example, using the structure of Figure 4B, 8 lines would be necessary to create the L2 coefficients from the L3 coefficients, 4 extra lines would be necessary to create the L1 coefficients from the L2 coefficients and 2 extra lines would be necessary to create the input tile from the L1 coefficients.

In one embodiment, to handle input tile data, a color conversion may be performed on the data prior to encoding. Figure 5 illustrates one embodiment of the process of handling the input data. Referring to Figure 5, color input pixels are received in raster order. These color pixels may be in RGB, YCrCb, CMY, CMYK, grayscale, etc. The color input pixels may be stored as tiles in a memory, such as memory 501, by band (or other forms).

Pixels from storage 501 or received directly from the input undergo color conversion and/or level shifting, with the resulting outputs being stored in one coefficient buffers 502_1 - 502_N . That is, once the color conversion has been completed on each tile, it is stored in one of the coefficient buffers 502_1 - 502_N , and then the next tile can be processed. In one embodiment, there is one coefficient buffer for each component.

Coefficient buffers 502_1 - 502_N are used by the transform in the manner described above to perform the wavelet transform while reusing memory. Thus, coefficient buffers 502_1 - 502_N are both input and output to wavelet transform.

- 5 After the transform is applied to coefficient buffers 502_1 - 502_N , the context model 503 and entropy coder 505 can perform further compression processing on the already transformed data. The coded data is buffered in coded data memory 505.

- 10 While performing the further compression processing on one tile, the transform may be applied to another tile. Similarly, any or all the operations may be performed on multiple tiles at the same time.

Progression Order Conversion

- 15 In the JPEG2000 standard, data in a compressed codestream can be stored in one of the five progression orders. The progression order can change at different points in the codestream. The order is defined by embedded "for layers" on layers, precincts, resolution, and components.

Five progression orders are described in the standard in Table A-16 of the JPEG 2000 standard. They are layer-resolution-component-position

progression (LRCP), resolution-layer-component-position progression (RLCP), resolution-position-component-layer progression (RPCL), position-component-resolution-layer progression (PCRL), component-position-resolution-layer progression (CPRL).

- 5 The order may be defined in the COD or POC markers of the JPEG 2000 standard. The Coding style default (COD) marker is defined by the JPEG 2000 standard and describes the coding style, number of decomposition levels, and layering that is the default used for compressing all components of an image (if in the main header) or a tile (if in a tile-part
- 10 header). The Progression order change (POC) marker describes the bounds and progression order for any progression order other than that specified in the COD marker segments in the codestream. The Packet Length Main Header (PLM) indicates a list of packet lengths in tile-parts for every tile part in order and the Packet Length, Tile-part header (PLT) indicates tile packet
- 15 lengths in a tile-part and indicates where the data is in the codestream.

The JPEG 2000 standard in section B.12 only specifies how packets of compress data are formed for a given progression order. It does not describe how data should be converted from one progression order to another progression order.

In one embodiment, a progression order converting parser converts a codestream to a desired progression order based on the user input without decoding the data and then encoding it again. Figure 6A illustrates a system having such a parser. Referring to Figure 6A, parser 601 receives requests from a client for a particular progression order. The client may be viewing a web page and selects a particular link. In response to the request, parser 601 accesses server 602 to obtain the codestream associated with full image 603 from memory 604 and converts the codestream into a different progression order based on the request. The request indicates the progression order by using an optional command (e.g., RL2L (Resolution-layer progression to Layer Progression)). The progression order that is described may be based on layer, resolution, component, precinct, or tile.

Figure 6B illustrates the progression converter converting from a layer progressive codestream (LRCP) to a resolution progressive (RLCP) codestream. The progression orders map directly to each other.

Figure 7A shows multiple ways to convert a codestream from one progression order to another. Referring to Figure 7A, each of the five progressions (LRCP, RLCP, RPCL, CPRL, and PCRL) are shown with paths to each of the others, such that all progressions are shown. In one

embodiment, the parser causes all conversions to go through the layer progression first and then to a selected conversion. Figure 7B shows one embodiment of such simplified conversion paths in which the number of required mappings is reduced from 10 (as in Figure 7A) to 4. However, any

5 one of the five progression orders could be used as the one to which all are converted before arriving at the selected order. The conversion technique described herein simplifies source codes in that the number of lines of source code is much less than the multiple ways of conversion. This results in less debug time and fewer memory and run-time variables.

10 To perform the conversion, the order of the packets in the codestream must be reordered. The packets are labeled by their sequential order in the codestream. Markers may indicate the starting point of the data, the length of the data (or alternatively the endpoint of the data) and how the data should be handled. For example, the indication of how the data is to be

15 handled may indicate whether the data is to be deleted, whether the data is to be truncated, or some other operation to be performed on the data. Such handling information may also come from rate distortion information, such as may be provided in a PLT/PLM and/or the PPT/PPM marker sets of the

JPEG 2000 standard. In this manner, the codestream may be truncated without changing the packet header.

In one embodiment, a list, array, or other structure (such as reordering structure 601A) is built by indicating the portion of data in each
5 packet. Using this structure, the packets may be reordered.

Figure 8 illustrates one embodiment of a process for performing progression order conversion. The process is performed by processing logic that may comprise hardware (e.g., dedicated logic, circuitry, etc.), software (such as is run by, for example, a general purpose computer or dedicated
10 machine), or a combination of both.

Referring to Figure 8, the process begins by processing logic building a list from headers in the packets (processing block 801) and optionally marking list items "delete" for quantization (processing block 802). Next, processing logic reorders the list to map the original progression to a desired
15 progression (including handling input and output with progressions specified with POC markers (bounds on the progression order) (processing block 803). Thereafter, processing logic outputs coded data based on reordered list (processing block 804).

Therefore, the combination of re-ordering and parsing allows specification of the desired ordering and resolution, quality, etc.

A Progression Order Conversion Example

5 The following is an example showing how packets are arranged in a codestream. The codestream was formed based on 2 components, 2 layers, 3 decomposition levels, and layer progression.

Table 4 shows the packet order, length and association index of packets in the example. The packet order column shows the sequential
10 order of packets placed in a codestream. The length indicates the length of the packets. The association index shows the resolution, layer, component, and precinct of the packet.

For example, packet[0] is the first packet in the codestream after the first tile header. It has a length of 589 bytes. Association index RwLxCyPz
15 indicates the packet belongs to resolution w, layer x, component y and precinct z.

Table 4

Packet order	Length	Association Index
packet[0]	length=589	R0L0C0P0
packet[1]	length=589	R0L0C1P0
packet[2]	length=924	R1L0C0P0
packet[3]	length=924	R1L0C1P0
packet[4]	length=1602	R2L0C0P0
packet[5]	length=1602	R2L0C1P0
packet[6]	length=733	R3L0C0P0
packet[7]	length=733	R3L0C0P0
packet[8]	length=535	R0L1C0P0
packet[9]	length=535	R0L1C1P0
packet[10]	length=1523	R1L1C0P0
packet[11]	length=1523	R1L1C1P0
packet[12]	length=5422	R2L1C0P0
packet[13]	length=5422	R2L1C1P0
packet[14]	length=16468	R3L1C0P0
packet[15]	length=16468	R3L1C1P0

In this codestream, packets are grouped based on the layer in which they reside. The first 8 packets belong to Layer 0. The following 8 packets

5 belong to Layer 1.

Using the conversion process described herein, the above codestream is converted to resolution layer progression. The following shows how the above packets are re-ordered.

After the layer progressive codestream is converted to resolution

10 progression, in the new codestream, packets are grouped based on

resolution. Such a grouping is shown in Table 5. The first 4 packets belong to resolution 0, the next 4 packets to resolution 1, and so on.

Table 5

Previous Packet order	Packet order	Length	Association Index
0	packet[0]	length=589	R0L0C0P0
1	packet[1]	length=589	R0L0C1P0
8	packet[2]	length=535	R0L1C0P0
9	packet[3]	length=535	R0L1C1P0
2	packet[4]	length=924	R1L0C0P0
3	packet[5]	length=924	R1L0C1P0
10	packet[6]	length=1523	R1L1C0P0
11	packet[7]	length=1523	R1L1C1P0
4	packet[8]	length=1602	R2L0C0P0
5	packet[9]	length=1602	R2L0C1P0
12	packet[10]	length=5422	R2L1C0P0
13	packet[11]	length=5422	R2L1C1P0
6	packet[12]	length=733	R3L0C0P0
7	packet[13]	length=733	R3L0C1P0
14	packet[14]	length=16468	R3L1C0P0
15	packet[15]	length=16468	R3L1C1P0

5 One Embodiment of a Conversion Algorithm

Resolution to Layer Progression

```

n = 0;
10  for(l=0;l<layer;l++){
      for(r=0;r<resolution+1;r++){
        for(c=0;c<component;c++){
          new_packet[n] = old_packet[l*component + r*layer*component +
c];          n++;

```

```

    }
  }
}

```

5

Layer to Resolution Progression

```

n = 0;
for(r=0;r<resolution+1;r++){
10   for(l=0;l<layer;l++){
        for(c=0;c<component;c++){
            new_packet[n] = old_packet[r*component +
                l*(resolution+1)*component + c];
            n++;
15         }
    }
}

```

20 where layer = the number of layers in a codestream,
 resolution = the number of decomposition levels in a codestream, and
 component = the number of components in a codestream

Data Hiding (Sideband Information) in JPEG2000 Coding

25 Bit hiding allows sideband information to be transmitted without
 increasing the file size. Sideband information that does increase file size but
 does not break naive decoders might also be valuable (although the COM
 marker defined by the JPEG 2000 standard might be used instead).

Some marker segments, packet headers and packets are padded out
 to the nearest byte. Examples of the JPEG 2000 marker segments include
 30 PPM, PPT, PLM, and PLT. In addition, some marker segments can be longer

than they need to be including QCD, QCC, and POC. In all of these cases, the padded data values are not defined.

Several proprietary coding schemes could use this semi-randomly located undefined data to provide a number of important types of information including, but not limited to, decoding and filtering hints, ownership, segmentation hints, and so on. A hint might include an index to a particular enhancement scheme. For example, if it is known that an image is mostly text, a value may be sent that indicates that a first post-processing filter is to be used. On the other hand, if the area is mostly a graphic image, then a value may be sent that indicates that a second post-processing filter is to be used.

The following are places where bits may be hidden or sideband information may be stored in the codestream.

- arithmetic coder (AC) termination (without predictable termination)
- end of packet header rounding to byte
- after last packet, before next tile
- tag tree construction by not always using minimum
- packet header Lblock signalling
- LSB parity for codeblocks (refinement pass only, cleanup pass only, all)
- QCD, QCC extra subbands, POC.

For example, with respect to hiding data using AC termination, 0 to 7 bits are provided, at least, everytime the coder is terminated. However, this could be extended for a few bytes. These extra bits and bytes may be used for sending extra information.

- 5 With respect to each packet header, the end of a packet header is rounded to a byte boundary. Therefore, there may be 1 to 7 bits that may be available for sending extra information at times when rounding would have been necessary. Similarly, each packet is rounded to a byte boundary, thereby providing 1 to 7 bits (assuming that rounding would have been
- 10 necessary). Also the last packet in a tile-part can be extended a few bytes. These extra bytes may be used to send additional information.

- 15 The length of the compressed data for a code-block can be given in the packet header with a non-minimum representation. The choice of representation (e.g., a non-minimum representation) could be used for indicating other information.

With respect to tag tree data hiding, packet headers of the JPEG 2000 standard use tag trees for coding first inclusion and zero bitplane information. When there are multiple codeblocks, tag trees are like a

quadtree of minimum values. For example, in the case of 16 codeblocks in a 4x4 arrangement in a packet, the arrangement may be as follows:

5 10 7 12 15
 3 20 21 5
 81 45 5 9
 18 8 12 24

10 An example tag tree, which is minimal for the 4x4 arrangement above is as follows:

15 3 0 2 7 4 7 10
 5 2 0 17 16 0
 73 37 0 4
 10 0 7 19

in which "3" is added to every codeblock's value, and "0", "2", "5" and "2" are each added to the 4 corresponding codeblocks. Finally, there is one value per codeblock. That is, the minimal tag tree is created by taking the first 2x2 group in the 4x4 arrangement above and look at minimum value is out of the four values. In this case, for the 2x2 block

10 7
 3 20

25 the minimum value is 3. This is then performed on the other 2x2 blocks. Then these identified minimum values are evaluated again to determine their minimum, which would be "3" in the example. Then the minimum value is subtracted from the four minimum values to create the following

0 2
5 2

Then, for the remaining numbers in the 4x4, the number 3 is subtracted from each value along with the value in the 2x2 that corresponds to the particular value in the 4x4 arrangement, thereby resulting in the tag tree above.

The first row adds up as follows:

10 = 3 + 0 + 7
7 = 3 + 0 + 4
12 = 3 + 2 + 7
15 = 3 + 2 + 10

A variable length code may be used that efficiently represents small numbers.

An example of a tag tree that is not minimal is as follows:

2 1 3 7 4 7 10
6 3 0 17 16 0
73 37 0 4
10 0 7 19

(Note that representing "3", "0", "2", "5" and "2" might use less bitstream data than "2", "1", "3", "6" and "3".)

Once a tag tree representation has been made, a determination can be made as to whether the representation is minimal or not based on whether there is a zero in the 2x2 block. Therefore, this information is hidden. For example, the 1 bit block represents the 1 in the 2x2 block above indicates it is

not part of a minimal tag tree, but can be used to convey some particular information to a decoder. Likewise if a 2 was the minimal value in the 2x2 block, such a fact may convey different information to a decoder.

The JPEG 2000 POC, QCD, and QCC markers can have redundant entries. It is as if the codestream were quantized and the markers were not rewritten. For example, the QCD and QCC markers have values for a number of subbands specified by the syntax of the marker. If there are fewer subbands actually coded in the bitstream, data may be hidden in the values used for the missing subbands. The redundant entries may be replaced and used for hidden or sideband information.

The hidden or sideband information may include post-processing hints (such as, for example, sharpen this tile with a specified filter or strength, or smooth, or perform optical character recognition (OCR) on this region, etc.), decoding hints, security (such as, for example, an encryption key for decoding the remainder of the image or another image, etc.) codestream identification (such as, for example, labeling POTUS as the originator of the file, etc.) and/or other information.

Use of Layers When Encoding

Layers are part of the JPEG standard. In one embodiment, sideband information, possibly in a COM marker, is used by the decoder to allow selecting of layers during decoding. The sideband information may be used

5 to select layers for postcompression quantization to meet rate/distortion targets for different viewing distances, different resolutions, different regions of interest, different frequency content for analysis (e.g., finding edges of text).

In one embodiment, the layers are predefined based on rate. For

10 example, the first layer represents a 1-bit per pixel image, while the second layer represents a 2-bit per pixel image, etc. Therefore, the layers run from the lowest quality to the highest quality. Likewise, target rates can be met for lower resolutions as well.

The sideband information may be stored in a marker segment of the

15 codestream. In one embodiment, the JPEG 2000 comment (COM) marker is used to provide information about the layers. Specifically, the COM marker may be used to indicate the number of bytes for each resolution and/or rate across the entire image or a relative number of bytes for each additional

layer. Table 6 indicates each layer and its resolution in the number of bytes across the tile in an image. Such a table may have distortion values instead.

Table 6

lev=0	layer=0	comp=0	bytes=529
lev=0	layer=0	comp=1	bytes=555
lev=0	layer=0	comp=2	bytes=493
lev=0	layer=1	comp=0	bytes=129
lev=0	layer=1	comp=1	bytes=130
lev=0	layer=1	comp=2	bytes=123
lev=0	layer=2	comp=0	bytes=7
lev=0	layer=2	comp=1	bytes=8
lev=0	layer=2	comp=2	bytes=12
lev=0	layer=3	comp=0	bytes=1
lev=0	layer=3	comp=1	bytes=1
lev=0	layer=3	comp=2	bytes=129
lev=1	layer=0	comp=0	bytes=705
lev=1	layer=0	comp=1	bytes=898
lev=1	layer=0	comp=2	bytes=712
lev=1	layer=1	comp=0	bytes=146
lev=1	layer=1	comp=1	bytes=114
lev=1	layer=1	comp=2	bytes=116
lev=1	layer=2	comp=0	bytes=224
lev=1	layer=2	comp=1	bytes=250
lev=1	layer=2	comp=2	bytes=263
lev=1	layer=3	comp=0	bytes=201
lev=1	layer=3	comp=1	bytes=212
lev=1	layer=3	comp=2	bytes=200
lev=2	layer=0	comp=0	bytes=889
lev=2	layer=0	comp=1	bytes=1332
lev=2	layer=0	comp=2	bytes=1048
lev=2	layer=1	comp=0	bytes=240
lev=2	layer=1	comp=1	bytes=329
lev=2	layer=1	comp=2	bytes=328
lev=2	layer=2	comp=0	bytes=599
lev=2	layer=2	comp=1	bytes=767

lev=2	layer=2	comp=2	bytes=725
lev=2	layer=3	comp=0	bytes=335
lev=2	layer=3	comp=1	bytes=396
lev=2	layer=3	comp=2	bytes=420
lev=3	layer=0	comp=0	bytes=1
lev=3	layer=0	comp=1	bytes=395
lev=3	layer=0	comp=2	bytes=402
lev=3	layer=1	comp=0	bytes=251
lev=3	layer=1	comp=1	bytes=450
lev=3	layer=1	comp=2	bytes=562
lev=3	layer=2	comp=0	bytes=525
lev=3	layer=2	comp=1	bytes=990
lev=3	layer=2	comp=2	bytes=1313
lev=3	layer=3	comp=0	bytes=1214
lev=3	layer=3	comp=1	bytes=1798
lev=3	layer=3	comp=2	bytes=2585

In another embodiment, the ordering could be by layer. Thus, the information above is consolidated for each level (not segregated by level or component), as shown below:

5

Ordering by layer=0 bytes=7959 bitrate=0.971558 PSNR=30.7785
Ordering by layer=1 bytes=10877 bitrate=1.327759 PSNR=32.0779
Ordering by layer=2 bytes=16560 bitrate=2.021484 PSNR=35.7321

10

Distortion by layers can be based on PSNR. For example,

layer=0 PSNR=30.7785
layer=1 PSNR=32.0779
layer=2 PSNR=35.7321

15

In an alternative embodiment, such information may be hidden in the codestream as described above. The information may be used to control rate distortion.

5 In another embodiment, the layers may be predefined for a particular viewing distance. In such a case, the data is divided into layers from the highest frequency, lowest resolution to the lowest frequency, highest resolution.

10 In one embodiment, the layer information indicates the summation of bits across the entire image for that layer and all previous layers (for example the 16,011 bits listed next to layer 1 indicates the total number of bits for layer 0 and layer 1). Alternatively, bytes, words, kilobytes, or other units of memory or rate could be used instead of bits. Table 7 shows this type of absolute rate information.

15 Table 8 shows relative rate information. Layer 0 has 4096 bits, layer 1 has 11,915 bits, etc.

Table 7

layer	Rate (bytes)
0	4,096
1	16,011
2	40,000
3	100,000
4	250,000
5	500,000
6	1,000,000
7	2,500,000
8	5,500,000

Table 8

layer	Rate (bytes)
0	4,096
1	11,915
2	23,989
3	60,000
4	150,000
5	250,000
6	500,000
7	1,500,000
8	3,000,000

5 For example, if only 750,000 bytes may be allowed in the decoded image, then all that can be decoded (as the 1,000,000 bytes tabulated with layer 6 includes the 500,000 bytes of layers 0-5) is through layer 5 and half of

importance layer 6. In some embodiments, no packets from layer 6 would be included. In other embodiments, some packets from layer 6 would be included and others would be replaced by zero packets so that the total amount of layer 6 data was approximately 250,000 bytes.

- 5 Figure 22 illustrates an example of layering for a 5,3 irreversible transform with three levels, MSE or similar. Referring to Figure 22, there are 45 layers shown. Each additional layer improves MSE in an order that gives good rate-distortion for MSE.

- 10 Figure 23 illustrates another example in which transform has 5 levels and the data is divided up into layers 0-3. Layer 0 corresponds to the thumbnail version, layers 0-1 correspond to the monitor (or screen) resolution, layers 0-2 correspond to the print resolution, and layers 0-3 correspond to lossless.

- 15 In an alternative embodiment, the layers may be predefined for some other distortion metric (e.g., MSE, weighted MSE, sharpness of text, etc.)

The decoder uses the information regarding the layers from the codestream to select layers to generate an image. The decoder knowing what the desired viewing characteristics from the application or implementation (see Table 9 below), and using the information from the

codestream specifying the layers, can quantize the codestream in order to display an image at the correct viewing distance. Figure 9 illustrates such a decoder. Referring to Figure 9, decoder 901 receives a codestream and includes quantization logic 902 that examines the COM marker and uses information about the viewing distance it is at stored in storage 903 to generate quantized codestream 904 via, for example, selecting the proper layers. Quantized codestream 904 is decoded by decoding logic 905 (e.g., a JPEG 2000 decoder) after selecting layers to generate an image data 906. A naive decoder would simply ignore the data in the comment marker.

Figure 10 is a flow diagram of a process for using layers when decoding. The process is performed by processing logic that may comprise hardware (e.g., dedicated logic, circuitry, etc.), software (such as is run by, for example, a general purpose computer or a dedicated machine), or a combination of both.

Referring to Figure 10, the process begins by processing logic receiving a codestream of compressed logic data (processing block 1001). The image data is organized into multiple layers, each of which comprises coded data that adds visual value to the image (e.g., look sharper, better defined, better contrast, etc.). Next processing logic selects one or more

layers for quantization based on sideband information (processing block 1002). After selection, processing logic decompresses the non-quantized layers of the codestream (processing block 1003).

5 Editing of Tiles, Tile-parts, or Packets

Once a codestream is created, it may be desirable to edit parts of the image. That is, for example, after performing encoding to create the codestream, a set of tiles may be decoded. After decoding the set of tiles, editing may be performed, followed by encoding the set of tiles with the edits to the same size as the encoded tiles were prior to their decoding. Examples of typical editing include sharpening of text and removing “red-eye.” The JPEG 2000 codestream can be edited in memory or in a disk file system without rewriting the entire codestream.

Figure 11 is a flow diagram of one embodiment of an editing process. The process is performed by process logic that may comprise hardware (e.g., dedicated logic, circuitry, etc.), software (such as is run by, for example, a general purpose computer or a dedicated machine), or a combination of both.

Referring to Figure 11, processing logic initially determines the tiles, tile-parts, or packets that cover the area, resolution, components, and/or precincts to be edited and decodes them (processing block 1101). This determination may be made in response to a user selecting an area and/or working resolution. The determination may use editing information for a higher resolution to determine which parts or tiles cover the portion to be edited. Once decoding has been completed, processing logic performs the desired edits (processing block 1102).

After performing the desired edits, processing logic recompresses the data into coded data (processing block 1103) and creates a replacement tile, tile-part, or packet for the codestream (processing block 1104). In one embodiment, in creating the replacement tile, tile-part, or packet, processing logic pads out the data with bytes at the end of the codestream if the new data is smaller than the unedited version of the data to make the replacement tile, tile-part or packet the same size as the unedited version.

In an alternative embodiment, processing logic may use a marker, or tag, such as a COM marker segment of the appropriate length instead of the padding. The COM marker could be used to fill space or could contain information that the encoder wanted to include. It could contain

information such as, for example, sideband information described herein or a copyright license for an image or text or other file format information.

In one embodiment, in creating the replacement tile, tile-part, or packet, processing logic truncates the last packets for any or all components
5 until the data fits in the codestream if the new data is larger than the unedited version of the data.

Editing of an image may be performed by changing coded data for tiles, tile-parts, or codeblocks. In one embodiment, editing is performed without changing file size by quantizing instead of expanding. In another
10 embodiment, a predetermined amount of extra space is allocated per tile or per codeblock to allow for a predetermined amount of expansion. In still another embodiment, coded data may be put at end of files by manipulating tile headers and putting invalid tile data in COM markers.

Note that if there are subsequent tile-parts that depend on the data in
15 the portion of the codestream that is being edited, these tile-parts may become useless in the codestream. An indication of this useless data may be noted to the decoder by one of several methods. These methods involve inserting or modifying information in the codestream to indicate the presence and/or location of the useless data. In one embodiment, the

application uses a status buffer to indicate that the data in tile-parts subsequent to an edited tile-part may be useless. The status buffer may be in workspace memory and describes dependencies between packets. If an earlier packet is altered, the subsequent packets cannot be decoded as is.

- 5 These subsequent packets must be edited accordingly or eliminated. In another embodiment, such an indication may be made by zeroing out the data section of those tile-parts and/or creating a PPT marker segment that denotes no data.

10 **Optimal Encoder Quantization**

During encoding, unquantized coefficients from some or all subbands may be divided by a value of Q to create the quantized coefficient values.

- This value Q may have a wide range of values. Typical encoders quantize a number of the values in a single particular range of values is made equal to
- 15 one single coefficient value. In essence, all the coefficients in the particular range are quantized to the same value. This can be exemplified by Figure 12 which shows that the range of values is often in a bell shaped curve and that all of the values in the particular range, such as range R_1 are sent to the decoder as one quantized value, such as R_1' , and the decoder will reconstruct

these values to a particular value. Assume a decoder reconstructs these values to a predetermined value (e.g., floor ($\frac{1}{2}$ min + $\frac{1}{2}$ max), or min + $\frac{1}{2}$ Q, where Q is the quantization step size). For example, if the range of values is between 16 and 31, then the decoder may assume the value is 24. In one

5 embodiment, instead of using $\frac{1}{2}$ as the value, another value is selected, such as floor ($\frac{3}{8}$ min + $\frac{5}{8}$ max), or min + $\frac{3}{8}$ Q, where Q is the quantization step size. Therefore, if the range is from 16 to 31, then it is assumed that the decoder will reconstruct the value to 22, instead of 24.

In some cases, two spatially adjacent coefficients may be close to each

10 other numerically yet in separate quantization bins, such as coefficient values 1201 of range R_2 and 1202 of range R_1 in Figure 12. The results of the quantization may cause an artifact to occur. In one embodiment, for coefficients near a boundary between two quantization bins, the encoder selects a bin such as Range R_1 into which a coefficient, such as coefficient

15 1201, will be quantized so that it is consistent with neighbors, such as coefficient 1202. This helps avoid artifacts. That is, this technique reduces distortion yet may increase rate, particularly when a coefficient is moved from a smaller bin to a higher bin.

Flicker Reduction for Motion JPEG

At times, flicker occurs when applying wavelet compression to motion sequences. An example of such flicker may include the image getting brighter or darker in areas or the appearance of edges changing in successive frames as the motion sequence is played (mosquito noise around the edges). The flicker may be due to the application of different local quantization to successive frames of a motion sequence or to noise exacerbated by quantization that is viewed temporarily.

To reduce flicker, coefficients that are in the same position and close to the same value in successive frames are forced to the same value. That is, the coefficients values in successive frames are set to a predetermined value. This is essentially a form of quantization that is applied during encoding. Figure 13 is a flow diagram of one embodiment of a process to reduce flicker.

A test of whether to apply such quantization to a coefficient value in a subsequent frame is based on the quantization that was performed on the coefficient in the previous frame. Thus, the encoder is utilizing frame dependency to eliminate flicker while the decoder decodes data frame by frame independently.

In one embodiment, in order to reduce flicker in motion JPEG, coefficient values are modified (quantized) based on their relationship with each other with respect to a threshold. For example, if D_n and D_{n+1} are the corresponding coefficient (same spatial location and same subband) in two frames before quantization, if D'_n and D'_{n+1} represent these coefficients after quantization, if $Q(\bullet)$ are scalar quantization, and if the value T is a threshold, then the following may be applied:

if ($|Q(D_{n+1}) - (D'_n)| < T$)
 $D'_{n+1} = D'_n$
 10 else
 $D'_{n+1} = Q(D_{n+1})$

For example, the value T may be twice the quantization step size. Other values of T include, but are not limited to, $\sqrt{2}Q$, $1.5Q$, $2\sqrt{2}Q$.

15 One of the coefficient values may be modified to be either a predetermined closeness to another coefficient value. The closeness may be determined by some threshold. The threshold may be user set or adaptive based on some criteria. The threshold could be different based on the subband and, perhaps, on the persistence of the particular value (number of frames that this coefficient is close). In one embodiment, the coefficient value is set equal to the other coefficient value. In alternative embodiments,

20

the coefficient is set to be within the quantization bin size of the other coefficient value or twice the quantization bin size.

Figure 14 illustrates one embodiment of an encoder (or portion thereof) that performs the quantization described above. Referring to Figure 14, a quantizer 1400 receives coefficients 1410 for frames of a motion sequence from a wavelet transform (not shown). The coefficients are received by quantization logic 1401 which compares a threshold value stored in memory 1401 to coefficient values for the previous frame that are stored in memory 1403 to coefficients 1410 with a scalar quantizer Q applied from memory 1404.

Quantization logic 1401 may comprise comparison hardware (e.g., logic with gates, circuitry, etc.) or software to perform the comparison. This comparison hardware and software may implement a subtractor or subtraction operation. The results are a quantized codestream (assuming some values have been changed.)

This may be applied over two or more frames. Also the comparison is not limited to two consecutive frames. The comparison can be over 3, 4, 5, etc., frames, for example, to determine if a variance exists. Figure 24

illustrates one example in which values in a first and third frame are used to set the value in the second frame.

Note that the quantization can also be codestream quantization with a code block-based rule.

5

Rate Control, Quantization, and Layering

In one embodiment, selective quantization of coefficients can be performed during encoding by setting a subset of the refinement bits to be the more probable symbol (MPS). This may be performed at a user selected bitplane. For examples, if there is text on a background image, with a goal of having sharp text images while minimizing coded data required for the background, the refinement bits that are set to MPS are those that do not effect text for the last bitplane, while using the actual value for bits that effect text.

15 Such a quantization scheme may be used to implement non-uniform quantization step sizes. For example, if one wanted to have a background with fewer bits, setting the refinement bits to the MPS could operate as a form of quantization. This quantization scheme causes some level of distortion but lowers the bit rate necessary to transfer the codestream.

Note that although this technique may be applied to bits generated during the refinement pass, the technique has application to other compression schemes (e.g., lists generated during subordinate passes, tail bits of CREW of Ricoh Silicon Valley, Menlo Park, California, MPEG IV texture mode, etc.).

In one embodiment, the same technique may be applied to other changes between frames. That is, in one embodiment, a change due to a rate distortion in one frame may be performed in a subsequent frame to avoid distortion effects.

10 *Rate Control and Quantization*

In one embodiment, user specified quantization is provided. For a 3 level transform for one component, 7 quantization values are sufficient: level 1 HH, level 1 HL and LH, level 2 HH, level 2 HL and LH, level 3 HH, level 3 HL and LH, and level 3 LH.

15 If quantization values are bitplanes to truncate (which is equivalent to scalar quantization by powers of 2), 3-bit values (0...7) are sufficient for most applications. (For image components with depth 12-bits or more and 5 or more transform levels, perhaps higher quantizations might be useful.) Values 0...6 could be used to specify the number of bitplanes to truncate and

7 could be used to mean discard all bitplanes. The three bit values may be written to a controller that controls compression (or decompression) hardware (e.g., JPEG2000 compatible hardware) to perform the quantization.

5 For 3 component color quantization:

- 21 values can be used with separate values for each component,
- 14 values can be used, 7 for luminance and 7 for chrominance,
- 17 values can be used for 4:1:1 subsampled data, 7 for luminance and 5 for each chrominance component,

10 • 12 values can be used for 4:1:1 subsampled data, 7 for luminance and 5 for chrominance,

- 19 values can be used for 4:2:2 subsampled data, 7 for luminance and 6 for each chrominance component, and

15 and 6 for chrominance.

Since $21 \times 3 = 63$ bits is less than 8 bytes, transferring or storing the quantization uses little resources. A central processing unit (CPU) might select one predetermined quantizer from a table and write it to a CPU or other controller controlling special purpose JPEG 2000 hardware (a chip) for

each frame of a motion JPEG 2000 video sequence. Alternatively, one implementation of JPEG 2000 might have a small memory that holds 8 or 16 different quantizers that could be selected for each frame.

Quantizers can also be used to assign bitplanes to layers. For example, Q_0 , Q_1 , and Q_2 may be quantizers that specify bitplanes of coding pass to quantize. Quantizer Q_0 causes the most loss, while quantizer Q_2 causes the least loss. Layer 1 is all the data quantized by Q_0 but not quantized by Q_1 . Layer 2 is all the data quantized by Q_1 but not quantized by Q_2 . Layer 3 is all the data quantized by Q_2 .

10

Simple Quantization

Figures 17 and 18 show example quantizers (label A...Q) for the 3-level 5/3 transform as the number of coefficient LSBs to truncate or not code. Truncating N bitplanes is equivalent to a scalar quantizer of 2^N . The subband where the quantization changes with respect to the previous quantizer is highlighted with a dashed box. The quantizers D, K and Q all have the same relationship between the subbands. Other quantizers might be used that are better for MSE or for other distortion metrics.

The exemplary Verilog below converts a single quantization value

“q” into seven quantizers (number of LSBs to truncate). The variable q_1_HH is used for level 1 HH coefficients, the variable q_1_H is used for level 1 HL and LH coefficients, etc. Some consecutive values of q result in the same quantizer: 0 and 1; 2 and 3; 4 and 5; $8i+6$ and $8i+7$ for all integers i

5 with $i \geq 0$.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203

```

module makeQ(q, q_1HH, q_1H, q_2HH, q_2H, q_3HH, q_3H,
q_3LL);
    input [5:0] q;
    output [3:0] q_1HH;
    output [3:0] q_1H;
    output [3:0] q_2HH;
    output [2:0] q_2H;
    output [2:0] q_3HH;
    output [2:0] q_3H;
    output [2:0] q_3LL;

    wire [3:0] temp_2H;
    wire [3:0] temp_3HH;
    wire [3:0] temp_3H;
    wire [3:0] temp_3LL;
    wire [2:0] qlo;
    wire [2:0] qhi;

    assign qlo = q[2:0];
    assign qhi = q[5:3];

    assign q_1HH = qhi + ((qlo >= 2) ? 1 : 0);
    assign q_1H = qhi + ((qlo >= 4) ? 1 : 0);
    assign q_2HH = qhi + ((qlo >= 6) ? 1 : 0);
    assign temp_2H = qhi + ((qlo >= 1) ? 0 : -1);
    assign temp_3HH = qhi + ((qlo >= 3) ? 0 : -1);
    assign temp_3H = qhi + ((qlo >= 5) ? 0 : -1);
    assign temp_3LL = qhi - 1;

    assign q_2H = (temp_2H < 0) ? 0 : temp_2H;
    assign q_3HH = (temp_3HH < 0) ? 0 : temp_3HH;
    assign q_3H = (temp_3H < 0) ? 0 : temp_3H;
    assign q_3LL = (temp_3LL < 0) ? 0 : temp_3LL;

endmodule

```

Table 9 shows additional bitplanes to quantize (e.g., truncate) for luminance to take advantage of the frequency response of the Human Visual System (from Table J-2 of the JPEG 2000 standard). A viewing distance of 1000 pixels might be appropriate for viewing images on a computer monitor.

- 5 Larger viewing distances might be appropriate for print images or television.

Table 9 - Human Visual System Weighting for Luminance

subband	extra biplanes to quantize for viewing distance of ...		
	1000 pixels	2000 pixels	4000 pixels
1HH	2	4 or 5	discard all
1HL, 1LH	1	2 or 3	6
2HH	—	2	4 or 5
2HL, 2LH	—	1	2 or 3
3HH	—	—	2
3HL, 3LH	—	—	1

- 10 Additionally chrominance may be quantized more heavily than luminance.

Figure 19 shows a quantization that starts with Figure 17(D) and then adds frequency weighting for a 1000 pixel viewing distance (to both luminance and chrominance), keeps 3LL chrominance unchanged, discards 1HL and 1HH chrominance for 4:2:2 and additional 2 bitplanes are

- 15 discarded for the remaining chrominance.

Sharp text without ringing artifacts is more desirable than exact gray value for text/background. That is, if a gray level is supposed to be at 50%

(for example), and is instead at 60%, it is often not visually objectionable if the image is of text. In one embodiment, the LL (DC) coefficients are quantized more heavily for text than for non-text images at low bitrate. For example, for an 8-bit image component, a quantization step size of 8, 16 or 32 might be used for text only regions and a quantization step size of 1, 2 or 4 might be used for regions containing non-text. This allows more fidelity for the high frequency coefficients, thereby resulting in text with sharp edges.

Using Quantizers to Divide Things into Layers

Table 10 shows 16 example quantizers. Quantizer 15 is lossless. Quantizer 8 is the same as Figure 19. These can be used divide the subband bitplanes into layers.

Table 10

subband	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Y 1HH	all	all	6	6	5	5	4	4	3	3	2	2	1	1	0	0
Y 1HL,LH	6	5	5	4	4	3	3	2	2	1	1	0	0	0	0	0
Y 2HH	5	4	4	3	3	2	2	1	1	0	0	0	0	0	0	0
Y 2HL,LH	4	4	3	3	2	2	1	1	0	0	0	0	0	0	0	0
Y 3HH	4	4	3	3	2	2	1	1	0	0	0	0	0	0	0	0
Y 3HL,LH	4	3	3	2	2	1	1	0	0	0	0	0	0	0	0	0
Y 3LL	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
C ₁ 1HL,HH	HL and HH always discarded for 4:1:1 or 4:2:2 only															
C ₁ 1LH	all	all	all	all	6	6	5	5	4	4	3	3	2	2	1	0
C ₁ 2HH	all	6	6	5	5	4	4	3	3	2	2	1	1	0	0	0
C ₁ 2HL,LH	all	6	5	5	4	4	3	3	2	2	1	1	0	0	0	0
C ₁ 3HH	all	6	5	5	4	4	3	3	2	2	1	1	0	0	0	0
C ₁ 3HL,LH	all	5	5	4	4	3	3	2	2	1	1	0	0	0	0	0
C ₁ 3LL	all	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
C ₂ 1HL,HH	HL and HH always discarded for 4:1:1 or 4:2:2 only															
C ₂ 1LH	all	all	all	all	6	6	5	5	4	4	3	3	2	2	1	0
C ₂ 2HH	all	6	6	5	5	4	4	3	3	2	2	1	1	0	0	0
C ₂ 2HL,LH	all	6	5	5	4	4	3	3	2	2	1	1	0	0	0	0
C ₂ 3HH	all	6	5	5	4	4	3	3	2	2	1	1	0	0	0	0
C ₂ 3HL,LH	all	5	5	4	4	3	3	2	2	1	1	0	0	0	0	0
C ₂ 3LL	all	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0

Layer 0 contains all data not quantized away by quantizer 0. This

would be luminance data only: all of 3LL; all but 4 bitplanes of 2HL, 2LH,

5 3HL, 3LH and 3HH; all but 5 bitplanes of 2HH and all but 6 bitplanes of 1HL

and 1LH. Layer 1 contains all data not in layer 0 and not quantized away by

quantizer 1. This would be luminance bitplanes 5 for 1HL and 1LH, bitplane

4 for 2 HH, bitplane 3 for 3HL and 3LH; all 3LL chrominance; all but 5

bitplanes for chrominance 3HL and 3LH; and all but 6 bitplanes for

10 chrominance 2HL, 2LH and 3HH. Finally, layer 15 would contain the LSB of

1LH chrominance.

Rate Control with Multiple Layers and Tile-Parts

There several well known techniques for rate control in compression systems. The simplest method is to pick a distortion for every "unit" compressed (a unit may be an 8x8 block in JPEG, a frame in a motion sequence, a tile of a single image, a subband of a tile in a wavelet coded image, etc.). If the distortion selected leads to a bitrate higher than the desired average bitrate, the distortion allowed is increased for new units as they are compressed. If the distortion selected leads to a bit rate lower than the desired average bitrate, the distortion allowed is decreased for new units as they are compressed.

A more complex method buffers the compressed data from some number of "units." The bitrate and/or distortion for each unit at each distortion level is stored. Then the distortion to allow across all the units in the buffer is determined when the buffer is full. If the buffer is sufficient to contain the entire image, extremely high quality results can be obtained. In JPEG 2000, layers are designed to contain increments to quality. Thus, selecting a distortion can mean selecting the number of layers to use for each code block or tile. A complete description of this type of rate control is in,

David Taubman, "High Performance Scalable Image Compression with EBCOT," IEEE Transactions on Image Processing.

There are several disadvantages to this process. One disadvantage is that a buffer memory for the entire codestream is required. A second
 5 disadvantage is that the latency (time until any of the codestream is output) is high. A third disadvantage is that the second pass could take large amount of time.

To mitigate these problems, each tile of a JPEG 2000 codestream is encoded as described above with at least two layers. At the completion of
 10 encoding each tile, a number of packets (e.g., layer, resolution, precinct, tile-component) are output to the codestream as a complete tile-part. The remaining layers are stored in the buffer. A second pass through the remaining coded data in the buffer is optional. During this second pass, extra packets from each tile are appended to the codestream as complete tile-
 15 parts as space or time allows. If in a fixed-rate application, then only packets within the given rate are appended. If in a fixed time application, then only number of cycles allowed. One embodiment of this process is shown in Figure 15A. Thus, these can be the 2 complete tile-parts output for each tile.

Figure 15B illustrates a number of layers, layers 1-n. Layer 1 is output on the first pass, and the remaining layers are most likely below fixed-time or fixed-rate time limits. Layer 2 may be output on a second pass within fixed-time or fixed-rate requirements while achieving similar distortion over all the components.

The above process is advantageous in that it allows the buffer to store a fraction of the coded data, the first data can be output (transmitted or stored) sooner, and the second pass through the data can be faster because there is less data to process. Also less memory is required for buffering.

The criterion for selecting which packets go into the first set of tile-parts can be similar to any other rate control algorithm. In one embodiment, the rate of packets can be less than the desired average bitrate for the whole image. For example, if a final compressed bitstream at 2.0 bpp is desired, the first pass could place 1.5 bpp for every tile in the codestream, and buffer 1 bpp for every tile.

The second pass can select from the remaining data the packets to place in the second tile part of each tile. Thus, to obtain a 2.0 bpp average encoding, some tiles that had high distortion after the first pass could receive all the remaining data saved for the tile, while other tile parts which

had low distortion after the first pass might not have any additional data transmitted.

Rate Control for Compressed Codestream Data

5 Some rate control techniques described herein include rate control performed on a compressed codestream based on a request implemented by selecting some number of layers to keep in the codestream. A parser may be used to produce a new codestream which shows the bitrate based on layers. This bitrate is equal to or less than the bitrate specified by the request.

10 The parser may use a data structure referred to herein as a “packet structure.” Note that this data structure may be used for other purposes such as, for example, the versatile packet data structure described below. In one embodiment, the packet structure includes a packet start pointer and packet length. It also contains a tile number, a resolution, a component,

15 layer, and a precinct the packet belongs to. Finally, it also consists of a selection flag. This flag, when set to a predetermined value (e.g., 1), indicates if the packet is selected in the array for writing out to a new codestream.

In one embodiment, packets are read in sequential order from a codestream based on the progression order information indicated by the COD marker.

5 The number of bytes is computed based on the bitrate desired by the request. The number of bytes belonging to layer 0 is added up to a total. Then this total of bytes is compared with the number of bytes desired. If the total is less than the number of bytes desired, one additional layer is added to the total. The process continues until the total is equal to or greater than the number of bytes desired or all packets have been added.

10 During the process, those packets which have been added to the total, are marked as selected by the selection flag in the structure.

If the total is equal to the number of bytes desired, the addition process is stopped. If the total exceeds the number of bytes desired, the packets in the last layer added are subtracted from the total. This is done to
 15 guarantee that the bitrate is below the bitrate desired. Consequently, during the subtraction step, packets which have been subtracted from the total are marked unselected.

In one embodiment, the related markers such as SOT, COD, PLT are updated according to the request. Packets are written to the new codestream. The packet structure may be created using the following:

```

5  typedef struct _PACK_ {          /* packet structure */
    int      start;    /* packet starting point */
    int      length;   /* packet length */
    unsigned short t;   /* tile number the packet belongs to */
    unsigned short r;   /* resolution the packet belongs to */
10  unsigned short c;   /* component the packet belongs to */
    unsigned short l;   /* layer the packet belongs to */
    unsigned short p;   /* precinct the packet belongs to */
    unsigned char  select; /* selection flag */
    } Pack_t;

15

    /* Store packets from tp->tile[i].Size[j] array to the packet structure array
    */ /* Layer progression (LRCP) order */

20  if(progression_order == 0){

        j = 0;
        for(i=0;i<number_of_tile;i++){
            m = 0;
25  for(l=0;l<layer;l++){
            for(r=0;r<resolution+1;r++){
                for(c=0;c<component;c++){
                    for(p=0;p<precinct[r];p++){

30  tp->pk[j].start = tp->tile[i].pointer[m];
            tp->pk[j].length = tp->tile[i].Size[m];
            total_length += tp->tile[i].Size[m];

            tp->pk[j].t = i;
35  tp->pk[j].r = r;

```

```

        tp->pk[j].l = l;
        tp->pk[j].c = c;
        tp->pk[j].p = p;
        m++;
5      j++;
      }
    }
  }
10  num_packet[i] = m;
  }
}

```

Versatile Packet Data Structure

15 The same packet data structure described above can be used to facilitate other parsing options, once packets are read into the structure.

For resolution parsing, the packets which are to be excluded are marked unselected. For example, given a 4 resolution codestream, and a request is to produce a 3-resolution codestream, a parser marks all packets

20 which belong to resolution 4 unselected. Then the newly produced codestream contains only packets from resolution 1 up to resolution 3.

Similarly, for component parsing, progression conversion parsing, quality parsing can be performed step by step processing the packets in the structure.

The packet data structure can handle complex requests. For example, a request which requires the parser to produce a codestream which has a 3-resolution, 2-layer, and 1-component codestream.

5 Clipping After Each Inverse Transform

As a result of quantization performed on wavelet coefficients, the final decoded pixels are often outside of the original range of allowed pixels from the specified bit depth. Typically, these pixels are clipped to the original range so that further image processing or display devices can use the original bit depth.

For example, an eight bit image has pixel values between 0 and 255, inclusive. After lossy compression is used, the decoded image may contain values like -5 and 256. To provide an eight bit output, these values are clipped to 0 and 255 respectively. This clipping procedure always reduces pixel wise distortion because the original image did not contain pixels outside of the clipping bounds. This procedure is well known and recommend by the JPEG 2000 standard.

In addition to the bounds on the final output samples, there are bounds on the values coefficients can assume at the various stages of the

wavelet transform. Just as quantization can change the final decoded samples to lie outside the original bounds, quantization can change the partially transformed wavelet coefficients to lie outside their original bounds. If these coefficients are clipped to their original bounds, distortion will decrease.

- For example, after a horizontal (one dimensional) 5-3 reversible transform as specified by JPEG 2000 with 8 bit input samples, the maximum value of the low pass coefficient is +191, and the minimum possible value is -191. The high pass coefficient must be between -255 and 255 inclusive.
- 10 After the vertical one dimensional transform, the Low-Low coefficients are bounded by -286 and 287. Thus when decoding an eight bit image, when the first level low-low pass coefficients are generated (by the inverse wavelet transform from a higher level), the coefficients can be clipped to -286 and +287, and distortion will decrease. Likewise after the first level vertical
- 15 inverse transformation is done, the low pass coefficients can be clipped to -191, +191, and the high pass coefficients can be clipped to -255, 255.

For each subband, each filter, each transform level, and each image depth, there is a different maximum and minimum value for the coefficients. These maximum and minimum values can be computed by finding the

signal that leads to the maximum and minimum and running the forward compression system and recording the maxima. The signals that lead to extreme values come from inputs where each pixel is either a maximum or minimum. Which pixels should be maximum and which pixels should be minimum can be determined by convolving sequences which are -1 when the wavelet coefficient is negative and +1 when the wavelet coefficient is negative. For the 5-3 filter used in JPEG 2000 Part I, the low pass signal of interest is [-1 +1 +1 +1 -1] and the high pass signal is [-1 +1 -1].

The signal (image) which will generate the largest LL value is:

10	+1 - 1 - 1 - 1 +1
	- 1 +1 +1 +1 - 1
	- 1 +1 +1 +1 - 1
	- 1 +1 +1 +1 - 1
	+1 - 1 - 1 - 1 +1

15 (where +1 must be replaced by the input maximum (e.g., 255) and -1 must be replaced by the input minimum (e.g., 0).

For irreversible filters, it is not necessary to actually run the system to determine the maxima, simply convolving the wavelet coefficients is sufficient. For the reversible 5-3 filter, however, the floor function is used in the computation of coefficients and is also used to determine the correct maxima.

Note that this may be used for other filters (e.g., a 9-7 filter).

Figure 28 is a flow diagram of one embodiment of a process for applying an inverse transform with clipping on partially transformed coefficients. The process is performed by processing logic, which may comprise hardware (e.g., circuitry, dedicated logic, etc.), software (such as
5 that which runs on a general purpose computer system or a dedicated machine), or a combination of both.

Referring to Figure 28, processing logic applies a first level inverse transform to coefficients (processing block 2801). Thereafter, processing logic clips the partially transformed coefficients to a predetermined range
10 (processing block 2802). Next, processing logic applies a first level inverse transform to the clipped coefficients (processing block 2803) and clips the partially transformed coefficients to a predetermined range (processing block 2804), which is different than the range in processing block 2802. Again, processing logic applies a first level inverse transform to clipped
15 coefficients (processing block 2805) and clips the partially transformed coefficients to still another predetermined range (processing block 2806).

Simplified Colorspace Handling

A typical decoding process including color management is shown in Figure 25. Referring to Figure 25, a file with a file format (e.g., a file format described in the JPEG 2000 standard) containing a restricted ICC profile is provided to a decoding device. Decompression block 2501 decompresses the file by taking the codestream portion of the file and performing context modeling, entropy decoding, and applying an inverse wavelet transform, but does not perform color space operations. If the codestream indicates the RCT or ICT component transform should be used to decode the codestream, these will be performed by block 2502. That is, inverse RCT/ICT block 2502 takes the components and the "RCT Y/N" indication (RCT if yes, ICT is no) and performs the specified inverse transform and provides (non-display) RGB pixels. (If specified by the syntax, inverse level shifting is also performed.)

Finally, the ICC color profile from the file format along with information about the display device will be used to produce the output pixels.

Inverse ICC block 2503 receives the (non-display) RGB pixels and the ICC profile and applies an inverse color space transform to provide display RGB pixels.

Figure 26 illustrates one embodiment of a non-preferred camera encoder. Referring to Figure 26, a camera generates YCrCb pixels. A converter 2602 converts the YCrCb pixels to RGB pixels and provides those to a typical JPEG 2000 encoder. The encoder comprises a RCT to ICT converter 2603 followed by a compressor 2604. The compressor generates an ICC_A for codestream.

Figure 27 illustrates one embodiment of a simpler camera encoder. That is, instead of including RCT/ICT converter 2603 and compressor 2604, a simple camera encoder includes only compressor block 2702. Referring to Figure 27, a camera 2701 generates YCrCb pixels and provides them to compressor 2702. Compressor comprises a JPEG 2000 encoder without an RCT conversion and generates an ICC_B codestream with RCT equaling 1 (with syntax signaling that the inverse RCT should be used on decoding).

The relationship between ICC_B and ICC_A is given by the following equation:

$$ICC_B = ICC_A \circ YCrCb^{-1} \circ RCT$$

where \circ represents function composition.

Restricted ICC profiles are “syntaxes” for functions on pixels. A camera will typically write the same profile for all images, so ICC_B is computed offline, and copied into each output file. In a prior art system there must be HW for $YCrCb^{-1}$ and RCT/ICT which operates on every pixel.

5

Coding 4:2:2 and 4:1:1 Data as 4:4:4 Data with Quantization

The JPEG 2000 standard is typically used to handling data in a 4:4:4 format. It is not capable of describing how to reconstruct data in 4:1:1 or 4:2:2 formats in a 4:4:4 format for output. In one embodiment, when encoding 4:1:1 data, the encoder treats 1 HL, 1 LH and 1 HH coefficients as zero. When encoding 4:2:2 data, the encoder treats 1 HL and 1 HH coefficients as zero. Thus, with all information in the extra subbands quantized to zero, a decoder is able to receive the codestream in a way it expects. In other words, the encoded data resembles 4:4:4 data that has been heavily quantized.

10

15

File Order for Thumbnail, Monitor, Printer, and Full Resolution and Quality

20

Multiple images at multiple resolutions are important in many image processing situations. Depending on the application, a user may want to

select different images of different resolutions. For example, thumbnail images may be used as an index into a large number of images. Also, a screen resolution image may be the image used to send to a monitor for display thereon. A print resolution image may be of lower quality for
5 printer applications.

In one embodiment, a codestream of an image is organized into sections so that different versions of the image, such as, for example, a thumbnail version, a screen version, a print version and a lossless version, is progressive by quality.

10 In one embodiment, the packets are arranged such that certain packets correspond to particular resolutions such as a thumbnail. The combination of these packets with other packets represents the monitor resolution image, which when combined with other packets may represent the printer version, etc. Using the POC and tile parts, portions of a
15 codestream may be grouped together. For example, all the tiles of the thumbnail size may be grouped together followed by tiles for another resolution followed by tiles of another resolution, etc. Figure 21 illustrates an example progression with tile parts for a single server. Each tile's thumbnail is grouped in tile-parts at the beginning of a file. Figure 21A

illustrates that tile-part 2101 is the only portion that is used for a thumbnail image. Figure 21B illustrates that for a monitor resolution, tile-parts 2102-2104 have been included with tile-part 2101. Figure 21C illustrates that for a printer resolution, tile-parts 2105 and 2106 have been included with tile-
5 parts 2101-2104. Lastly, Figure 21D illustrates that for a lossless version of the data, the remaining three tile-parts 2107-2108 are included with the rest of the tile-parts. These sets of tile parts may be placed on a server in this progressive order.

One embodiment of the process for accessing the groupings of tile
10 parts is shown in Figure 16. The process may be performed by processing logic that may comprise hardware (e.g., dedicated logic, circuitry, etc.), software (such as is run on a general purpose computer system or a dedicated machine), or a combination of both. The following steps assume that the image has been transformed with sufficient resolution levels and
15 layers to divide the image into the four sizes.

Referring to Figure 16, processing logic initially determines the correct resolution and layering for the thumbnail (processing block 1601). In one embodiment, to determine the correct resolution and layering for the thumbnail, processing logic creates a POC constrained to that resolution and

layer for each tile and then creates a set of tile-parts and places this POC for each tile in the codestream.

Next, processing logic repeats processing block 1601 for the monitor resolution given that the thumbnail packets are already in the codestream (processing block 1602). Then, processing logic repeats processing block 1601 for the printer resolution given that the monitor packets are already in the codestream (processing block 1603).

Lastly, processing logic creates a POC marker with the extremes of the resolutions and layers for each tile (processing block 1604). In one embodiment, creating the POC with the extremes of the resolutions and layers is performed by creating a fourth set of tile-parts with the remaining tile-parts for a lossless version.

Note that the particular orders of the packets defined in the POCs are not of importance, only the limits.

An Exemplary Computer System

Figure 20 is a block diagram of an exemplary computer system. Referring to Figure 20, computer system 2000 may comprise an exemplary client 150 or server 100 computer system. Computer system 2000 comprises

a communication mechanism or bus 2011 for communicating information, and a processor 2012 coupled with bus 2011 for processing information.

Processor 2012 includes a microprocessor, but is not limited to a microprocessor, such as, for example, Pentium™, PowerPC™, Alpha™, etc.

- 5 System 2000 further comprises a random access memory (RAM), or other dynamic storage device 2004 (referred to as main memory) coupled to bus 2011 for storing information and instructions to be executed by processor 2012. Main memory 2004 also may be used for storing temporary variables or other intermediate information during execution of instructions
- 10 by processor 2012.

- Computer system 2000 also comprises a read only memory (ROM) and/or other static storage device 2006 coupled to bus 2011 for storing static information and instructions for processor 2012, and a data storage device 2007, such as a magnetic disk or optical disk and its corresponding disk
 - 15 drive. Data storage device 2007 is coupled to bus 2011 for storing information and instructions.

Computer system 2000 may further be coupled to a display device 2021, such as a cathode ray tube (CRT) or liquid crystal display (LCD), coupled to bus 2011 for displaying information to a computer user. An

alphanumeric input device 2022, including alphanumeric and other keys, may also be coupled to bus 2011 for communicating information and command selections to processor 2012. An additional user input device is cursor control 2023, such as a mouse, trackball, trackpad, stylus, or cursor
5 direction keys, coupled to bus 2011 for communicating direction information and command selections to processor 2012, and for controlling cursor movement on display 2021.

Another device that may be coupled to bus 2011 is hard copy device 2024, which may be used for printing instructions, data, or other information
10 on a medium such as paper, film, or similar types of media. Furthermore, a sound recording and playback device, such as a speaker and/or microphone may optionally be coupled to bus 2011 for audio interfacing with computer system 2000. Another device that may be coupled to bus 2011 is a
wired/wireless communication capability 2025 to communication to a
15 phone or handheld palm device.

Note that any or all of the components of system 2000 and associated hardware may be used in the present invention. However, it can be appreciated that other configurations of the computer system may include some or all of the devices.

Whereas many alterations and modifications of the present invention will no doubt become apparent to a person of ordinary skill in the art after having read the foregoing description, it is to be understood that any particular embodiment shown and described by way of illustration is in no way intended to be considered limiting. Therefore, references to details of various embodiments are not intended to limit the scope of the claims which in themselves recite only those features regarded as essential to the invention.
